

whirlwind

99 Ling Rd Rochester NY 14612
 800 733-9473 FAX - 585 865-8930
<http://www.whirlwindusa.com> - e-mail: sales@whirlwindusa.com

Standard Color Codes

Whirlwind Multipair Cable

TS	Gnd	Tip	Gnd
TRS	Ring	Tip	Gnd
XLR	Pin 3	Pin 2	Pin 1
Pair #	(-)	(+)	(g)
1	Black	Red	
2	Black	White	
3	Black	Green	
4	Black	Blue	
5	Black	Yellow	
6	Black	Brown	
7	Black	Orange	
8	Red	White	
9	Red	Green	
10	Red	Blue	
11	Red	Yellow	
12	Red	Brown	
13	Red	Orange	
14	Green	White	
15	Green	Blue	
16	Green	Yellow	
17	Green	Brown	
18	Green	Orange	
19	White	Blue	
20	White	Yellow	
21	White	Brown	
22	White	Orange	
23	Blue	Yellow	
24	Blue	Brown	
25	Blue	Orange	
26	Brown	Yellow	
27	Brown	Orange	
28	Orange	Yellow	
29	Purple	Orange	
30	Purple	Red	
31	Purple	White	
32	Purple	Green	
33	Purple	Blue	
34	Purple	Yellow	
35	Purple	Brown	
36	Purple	Black	
37	Gray	White	
38	Gray	Brown	
39	Gray	Red	
40	Gray	Green	
41	Gray	Orange	
42	Gray	Yellow	
43	Gray	Black	
44	Gray	Blue	
45	Pink	White	
46	Pink	Green	
47	Pink	Blue	
48	Pink	Yellow	
49	Pink	Brown	
50	Pink	Orange	
51	Pink	Purple	
52	Pink	Gray	
53	Beige	White	
54	Beige	Green	
55	Beige	Blue	
56	Beige	Yellow	
57	Beige	Brown	
58	Beige	Orange	

Whirlwind Speaker Cable

Pin #	Color
NL8 FC with W13/8 wire	
1+	Black
1-	White
2+	Red
2-	Green
3+	Brown
3-	Blue
4+	Orange
4-	Yellow

Pin #	Color
NL4 FC with W12/4 wire	
1+	Black
1-	White
2+	Red
2-	Green

NEW! ==> NL2 or NL4 with W12/2 wire

1+	Black
1-	White

Pin #	Color
EP8 with W13/8 wire	
1	Black
2	White
3	Red
4	Green
5	Brown
6	Blue
7	Orange
8	Yellow

Pin #	Color
EP6 with W13/8 wire	
1	Black
2	White
3	Red
4	Green
5	Brown
6	Blue

Pin #	Color
EP4 with W12/4 wire	
1	Black
2	White
3	Red
4	Green

All 2 Conductor W12/2 (Except NL2 & NL4)

+	White
-	Black

Power Series Speaker (14Ga)

+	Orange	Spkr 1
-	Red	
+	White	Spkr2
-	Green	

Canare MR202-AT Channel Color Code

UnitNo.	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32								
Insulator Color*	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED								
Spiral Marker	BRN	RED	ORN	YEL	CRN	ELU	PPL	GRY	WHT	BLK		RED	ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN		ORN	YEL	GRN	BLU	PPL	GRY	WHT	BLK	BRN	RED								
Inner Jacket Color	BLK										BRN										RED										ORG									

NOTE: Identify the conductor by Spiral Marker and color of Inner Jacket. *Insulator in the unit: one is same color as Spiral Marker and the other is clear.

Belden 8451, W1266A Belden Individually Jacketed Multipair West Penn W291

TS	Gnd	Tip	Gnd
TRS	Ring	Tip	Gnd
XLR	Pin 3	Pin 2	Pin 1
	(-)	(+)	(g)
	Black	Red	Gnd

Quad Cable

Accusonic +4 Belden W1192A Canare WL-4E6S

TS	Gnd	Tip	Gnd
TRS	Ring	Tip	Gnd
XLR	Pin 3	Pin 2	Pin 1
	(-)	(+)	(g)
	2	2	
	Blues	Whites	Gnd

Mogami 3162 8-pair

Core No.	Color
1	Brown
2	Red
3	Orange
4	Yellow
5	Green
6	Blue
7	Purple
8	Gray

Color of other wire in all pairs
is fluorescent green

Mogami W2552

TS	Gnd	Tip	Gnd
TRS	Ring	Tip	Gnd
XLR	Pin 3	Pin 2	Pin 1
	(-)	(+)	(g)
	Clear	Red	Gnd